

ORBOT SLiM

Lithium-ion Hybrid



Scan for more info

Designed for small spaces like bathrooms, hallways, and kitchens, this lightweight yet powerful machine fits easily under furniture and delivers outstanding deep cleaning. With its low-moisture technology, on-board solution tank, and quick change pad system, the ORBOT SLiM offers versatile floor cleaning.



CRI CERTIFIED



SPRAY SWITCH
Easy touch control

LEVER-FREE ON/OFF SWITCH
Continuous hands-free power

QUICK-CHANGE SOLUTION TANK
Holds 2.84 L capacity saving time & labour

CLEAR COAT PROTECTION
High-gloss finish for improved long-term durability

PUMP
58 PSI / 4 BAR

LITHIUM-ION BATTERY
36V, 6Ah, Runs up to 45 minutes, Battery Management System (BMS), Hybrid compatible *Fits into battery tray

LIFT HANDLE
Provides easy lifting & lowering of base

DC MOTOR
36V / 330W – DC, 3000 RPM, 59 dB with protective cover

WHEEL KIT
Improves maneuverability, reduces operator fatigue, and adds additional lift handle

SPRAY JET
Low moisture spray reduces water, chemical & labour

TRANSPORT WHEELS
10.16 cm DIA
Chemical-resistant & non-marking

LED LIGHTS
Illuminates dark areas

WEIGHT PLATE
Increased head pressure for maximum cleaning performance

QUICK-FLIP BASE
For quick pad changing

FREE FLOATING 11" BASE
Provides 100% contact on floors

Specifications

BASE DIAMETER 27.9cm | **MOTOR** 36V,330W DC | **DUAL RPM SPEED** Orbital 3000 RPM + Rotational 120 RPM | **LITHIUM-ION BATTERY** 36V / 216Wh / 6Ah | **RUN TIME** Up to 45 minutes (depending on floor/pad) | **CHARGE TIME** 90 minutes | **NOISE LEVEL** 59dB
WEIGHT 12.7 + 2.7kg w/tank & battery | **HEIGHT** 119cm | **SOLUTION TANK CAPACITY** 2.84L
PUMP 58PSI / 4 BAR

CODE	DESCRIPTION
ORB.SLM.0000B	ORBOT SLiM w/o battery
ORB.SLM.1100C	ORBOT SLiM with battery
120.0738.0	Scrub brush tiles/grout (1)
120.0728.0	Scrub brush carpet (1)
120.0726.0	Kit pad ultralift (5)
120.0727.0	Kit pad microfibre (5)
120.0747.0	Kit pad superzorb (10)
120.0719.0	Kit pad stoneflash (5)
S.120.1000.8	Charger
S.120.0311.0	Battery